

**Forced-air cooling: Blank type**


Front



Back



Dimension

L	*	W	*	H
460	*	211	*	83.5(2U) mm
18.1	*	8.3	*	3.29(2U) inch

**Water cooling: L type**


Front



Back



Ordering No.: HS-684

Dimension

L	*	W	*	H
460	*	216	*	83.5(2U) mm
18.1	*	8.5	*	3.29(2U) inch



UL62368-1



EN62368-1



TPTC004



IEC62368-1



EAC



CB



CE



UK




CA


**Features**

- 3  $\phi$  3-wire without Neutral / 340~530VAC wide input range
- High efficiency up to 97%
- Water / forced air cooling selectable
- Built-in CANBus/Optional PMBus/MODBus-RTU/RS-485 protocol
- Output voltage and constant current level programmable
- Active current sharing up to 4 units(40KW)
- Built-in remote ON-OFF control / Auxiliary power / Alarm signal
- Protections: Short circuit / Overload / Over voltage / Over temperature / Fan fail
- 5 years warranty

**Description**

SHP-10K-HV is a 10KW 3  $\phi$  3W input AC/DC power supply. This series operates for the wide range three phase AC input (3 phase 3 wire / 340~530VAC) neutral is not needed, and offers the models with DC outputs (55V/115V/230V/380V) that mostly demanded by various industries. Two types of cooling methods, forced air and water cooling, that can be working at ambient temperature up to 70°C. Moreover, SHP-10K-HV provides vast design flexibility by equipping various built-in functions such as output programming, active current sharing, remote ON-OFF control, auxiliary power, and communication protocols, that will not only satisfy market demand, but also enhance automation purpose.


**Model Encoding**


Type	Communication Protocol	Note
Blank	CANBus	In Stock
-PM	PMBus	By request
-MOD	MODBus-RTU/RS-485	By request

## SPECIFICATION


MODEL	SHP-10K-55		SHP-10K-115		SHP-10K-230		SHP-10K-380						
OUTPUT	DC VOLTAGE (factory default)	55V	115V	230V	380V								
	CURRENT (factory default)	131A	87A	43.5A	26.3A								
	CURRENT RANGE	0 ~ 150A	0 ~ 87A	0 ~ 46.3A	0 ~ 30A								
	RATED POWER (max.)	7200W	10000W	10000W	10000W								
	FULL POWER VOLTAGE RANGE	48 ~ 57.6V	115 ~ 138V	216 ~ 260V	334 ~ 400V								
	RIPLPE & NOISE (max.) Note.2	0.3Vp-p	0.6Vp-p	1Vp-p	1Vp-p								
	VOLTAGE ADJ. RANGE	39 ~ 57.6V	90 ~ 138V	170 ~ 260V	260 ~ 400V								
		Can be adjusted via built-in potentiometer											
	VOLTAGE TOLERANCE Note.3	±1.0%	±1.0%	±1.0%	±1.0%								
	LINE REGULATION	±0.5%	±0.5%	±0.5%	±0.5%								
INPUT	LOAD REGULATION	±0.5%	±0.5%	±0.5%	±0.5%								
	SETUP, RISE TIME	3000ms, 100ms at full load											
	HOLD UP TIME (Typ.)	25ms / 400VAC at 75% load		20ms / 400VAC at full load									
	VOLTAGE RANGE Note.5	3 $\phi$ 3-wire / 340 ~ 530VAC											
	FREQUENCY RANGE	47 ~ 63Hz											
PROTECTION	POWER FACTOR (Typ.)	≥ 0.98/400VAC/480VAC at full load											
	EFFICIENCY (Typ.) Note.7	94.5%	96%	96.5%	96.5%								
	AC CURRENT (Typ.)	11.2A/400VAC	9.5A/480VAC	15.7A/400VAC	13A/480VAC								
	INRUSH CURRENT (Typ.)	40A/400VAC											
	LEAKAGE CURRENT	<6.5mA peak / 530VAC											
	OVER LOAD	100 ~ 105% of rated current Protection type : Constant current limiting, unit will shutdown after 5 sec. re-power on to recover											
FUNCTION	OVER VOLTAGE	60.5 ~ 69.1V	145 ~ 166V	273 ~ 312V	420 ~ 480V								
	OVER TEMPERATURE	Protection type : Shut down o/p voltage, re-power on to recover											
	CURRENT SHARING	Up to 4 units. Please refer to the Function Manual											
ENVIRONMENT	OUTPUT VOLTAGE PROGRAMMABLE	Adjustment of output voltage is allowable between 50 ~ 120% of nominal output voltage. Please refer to the PV curve Function Manual											
	CONSTANT CURRENT LEVEL PROGRAMMABLE	Adjustment of constant current level is allowable between 20 ~ 100% of rated current. Please refer to the PC curve Function Manual											
	AUXILIARY POWER(AUX)	12V@1A tolerance ±5%, ripple 150mVp-p											
	REMOTE ON-OFF CONTROL	Please refer to the Function Manual.											
	ALARM SIGNAL OUTPUT	AC-OK, DC-OK, Fan Fail. Please refer to the Function Manual.											
	DC-OK SIGNAL	The TTL signal output, PSU turn on = -0.5 ~ 0.5V ; PSU turn off = 3.5 ~ 5.5V. Please refer to the Function Manual											
SAFETY & EMC (Note 6,8)	WORKING TEMP.	-30 ~ +70°C (Refer to "Derating Curve")											
	WORKING HUMIDITY	20 ~ 90% RH non-condensing											
	STORAGE TEMP., HUMIDITY	-40 ~ +85°C, 10 ~ 95% RH non-condensing											
	TEMP. COEFFICIENT	±0.03%/°C (0 ~ 50°C)											
	VIBRATION	10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes											
	SAFETY STANDARDS	UL62368-1, CAN/CSA C22.2 No. 62368-1, TUV BS EN/EN62368-1, EAC TP TC 004 approved											
	WITHSTAND VOLTAGE Note.4	I/P-O/P:3.75KVAC	I/P-FG:2KVAC	O/P-FG:1.25KVAC									
	ISOLATION RESISTANCE Note.4	I/P-O/P, I/P-FG, O/P-FG:100M Ohms / 500VDC / 25°C / 70% RH	Parameter		Standard	Test Level / Note							
	EMC EMISSION	Conducted	BS EN/EN55032 (CISPR32) / EN55011 (CISPR11)		Class B								
		Radiated	BS EN/EN55032 (CISPR32) / EN55011 (CISPR11)		Class A								
		Harmonic Current	BS EN/EN61000-3-2		-----								
		Voltage Flicker	BS EN/EN61000-3-3		-----								
EMC IMMUNITY	EN55024 , EN61204-3, EN61000-6-2			Parameter		Standard	Test Level / Note						
				ESD	BS EN/EN61000-4-2		Level 3, 8KV air ; Level 2, 4KV contact						
				Radiated	BS EN/EN61000-4-3		Level 3						
				EFT / Burst	BS EN/EN61000-4-4		Level 3						
				Surge	BS EN/EN61000-4-5		Level 4, 4KV/Line-Earth ; Level 3, 2KV/Line-Line						
				Conducted	BS EN/EN61000-4-6		Level 3						
				Magnetic Field	BS EN/EN61000-4-8		Level 4						
				Voltage Dips and Interruptions	BS EN/EN61000-4-11		>95% dip 0.5 periods, 30% dip 25 periods, >95% interruptions 250 periods						
OTHERS	MTBF	281.2K hrs min. Telcordia SR-332 (Bellcore) ; 28K hrs min. MIL-HDBK-217F (25°C)											
	DIMENSION	SHP-10K: 460*211*83.5mm (L*W*H) SHP-10K-L: 460*216*83.5mm (L*W*H)											
	PACKING	SHP-10K: 11.9Kg; 1pcs/11.9Kg/1.25CUFT SHP-10K-L: 11.9Kg; 1pcs/11.9Kg/1.1CUFT											
NOTE	<ol style="list-style-type: none"> <li>All parameters NOT specially mentioned are measured at 400VAC input, rated load and 25°C of ambient temperature.</li> <li>Ripple &amp; noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf &amp; 47uf parallel capacitor.</li> <li>Tolerance : includes set up tolerance, line regulation and load regulation.</li> <li>During withstand voltage and isolation resistance testing, the screw "A" shall be temporarily removed, and shall be installed back after the testing.</li> <li>Derating may be needed under low input voltages. Please check the derating curve for more details.</li> <li>Additional EMI filter is needed to meet regulations of EMC conducted and radiated emission. Characteristics of EMI filter please refer to the table, Minimum Insertion Loss.</li> <li>The efficiency is measured at 480VAC input.</li> <li>The power supply is considered a component which will be installed into a final equipment. All the EMC tests are been executed by mounting the unit on a 600mm*900mm metal plate with 1mm of thickness. The final equipment must be re-confirmed that it still meets EMC directives. For guidance on how to perform these EMC tests, please refer to "EMI testing of component power supplies." (as available on <a href="http://www.meanwell.com">http://www.meanwell.com</a>)</li> <li>The ambient temperature derating of 3.5°C/1000m with fanless models and of 5°C/1000m with fan models for operating altitude higher than 2000m(6500ft).</li> <li>If use PV signal to adjust Vo, under certain operations conditions, ripple noise of Vo might slightly go over rating defined in this specification.</li> <li>Under light load condition, output voltage ripple will exceed specification. The behavior can be minimized by increasing the load.</li> </ol> <p>※ Product Liability Disclaimer : For detailed information, please refer to <a href="https://www.meanwell.com/serviceDisclaimer.aspx">https://www.meanwell.com/serviceDisclaimer.aspx</a></p>												

## ■ BLOCK DIAGRAM





## ■ DERATING CURVE


Blank Type:




L Type:




L Type:



■ STATIC CHARACTERISTICS



■ EFFICIENCY VS LOAD (380V MODEL)



■ AC Power Connection

◎3  $\psi$  3-wire /  $\triangle$  340VAC~530VAC




Fig 1.1

◎3  $\psi$  3-wire / Y 340VAC~530VAC




Fig 1.2

## Function Manual

### 1. Output Voltage Programming (or, PV / remote voltage programming / remote adjust / margin programming / dynamic voltage trim)

(1) Default by potentiometer (SVR)



(a) Have the DIP switch position-3 set as 

(b) Output voltage can be trimmed by SVR.


(2) By Output Voltage Programming

(a) Have the DIP switch position-3 set as 

(b) The output voltage can be trimmed to 50~120% by applying EXTERNAL VOLTAGE between PV+ and PV- on CN53.



◎ The 100% output voltage is 48/115/216/334V.



◎ The rated current should change with the Output Voltage Programming accordingly.

Fig 1.2

## 2. Constant Current Programming (or, PC / remote current programming / dynamic current trim)


(1) Default Overload Protection(OLP) value



(a) Have the DIP switch position-2 set as ON

(b) Output current is set default value.

(2) By Constant Current Level Programming



(a) Have the DIP switch position-2 set as OFF

(b) The constant current level can be trimmed to 20~100% of the rated current by applying EXTERNAL VOLTAGE between PC+ and PC- on CN53.






Fig 2.1

※ Under PC function at wattage < 4KW, the power supply might enter burst mode and cause output unstable, please increase the load to minimized the effect.

※ Auto de-rating function covered by over temperature protection, it works either in PC mode or under control by communication protocol.

T1(Typ.): Maximum ambient temperature of full load.

T2(Typ.): T1+5°C.



◎ The 100% output current is 150/87/46.3/30A.

Fig 2.2

### 3.DA, DB signal and parallel control function

#### (1)Non-parallel operation

(a)set the DIP switch of postion-1 as



(b)By default, non-parallel operation.

#### (2)Default parallel operation

(a)set the DIP switch of postion-1 as



(b)PSUs are configured in parallel operation.




Fig 3.1

### 4.Remote ON-OFF Control

※ The power supply can be turned ON-OFF by using the "Remote ON-OFF" function.

Between Remote ON-OFF(CN86 pin1) and 5V-AUX(CN86 pin2)	Output Status
Switch close (Short)	power supply ON
Switch open (Open)	power supply OFF

Table 4.1




Fig 4.1

### 5. Alarm Signal Output

※ There are 4 alarm signals, DC-OK, T-ALARM, Fan Fail and AC-OK, in TTL signal form, on CN86. These signals are isolated from output.




Fig 5.1

※ DC OK might mis-triggered when the voltage difference between PSU and the load, please minimized the unnecessary voltage difference.

### 6. Current Sharing

SHP-10K has the built-in active current sharing function and can be connected in parallel, up to 4 units, to provide higher output power as exhibited below :

※ The power supplies should be paralleled using short and large diameter wiring and then connected to the load.

※ In parallel connection, power supply with the highest output Voltage will be the master unit and its Vout will be the DC bus voltage.

※ The total output current must not exceed the value determined by the following equation:

Maximum output current at parallel operation = (Rated current per unit)  $\times$  (Number of unit)  $\times$  0.95

※ When the total output current is less than 5% of the total rated current, or say (5% of Rated current per unit)  $\times$  (Number of unit) the current shared among units may not be balanced.

※ Under parallel operation ripple of the output voltage may be higher than the SPEC at light load condition. It will go back to normal ripple level once the output load is more than 5%.

※ CN53/SW1 Function pin connection

Parallel	PSU1		PSU2		PSU3		PSU4	
	CN53	SW1 PIN1						
1 unit	X	ON	—	—	—	—	—	—
2 unit	V	ON	V	ON	—	—	—	—
3 unit	V	ON	V	OFF	V	ON	—	—
4 unit	V	ON	V	OFF	V	OFF	V	ON

(V : CN53 connected ; X : CN53 not connected.)





Fig 6.1




If the lines of CN53 are too long, they should be twisted in pairs to avoid the noise.

◎ DA,DB are connected mutually in parallel.

## ■ Mechanical Specification


### ※ Forced-Air Cooling (Blank type)

Case No.223 Unit:mm




## ※ Mounting Instruction

Hole No.	Recommended Screw Size	MAX. Penetration Depth L	Recommended mounting torque
①	M4	5mm	7~10Kgf-cm




※ Water Cooling (L type)

Case No.223D Unit:mm



※ Control Pin No. Assignment (CN53) : HRS DF11-10DP-2DS or equivalent




Mating Housing	HRS DF11-10DS or equivalent
Terminal	HRS DF11-**SC or equivalent

1 9  
2 10

Pin No.	Function	Description
1,2	-V(Signal)	Negative output voltage signal. It is for local sense and certain function reference; it cannot be connected directly to the load.
3,4	PV+	Connection for output voltage programming. (Note)
5,6	PC+	Connection for constant current level programming. (Note)
7,8	DB	Differential digital signal for parallel control. (Note)
9,10	DA	Differential digital signal for parallel control. (Note)

Note: Non-isolated signal, referenced to [-V(Signal)].

※ Control Pin No. Assignment (CN86) : HRS DF11-18DP-2DS or equivalent



Mating Housing	HRS DF11-18DS or equivalent
Terminal	HRS DF11-**SC or equivalent

18 2  
17 1

Pin No.	Function	Description
1	Remote ON-OFF	The unit can turn the output ON/OFF by dry contact between Remote ON/OFF and +5-AUX.(Note) Short (4.5 ~ 5.5V) : Power ON ; Open(0 ~ 0.5V) : Power OFF ; The maximum input voltage is 5.5V
2	+5V-AUX	Auxiliary voltage output, 4.5~5.5V, referenced to GND-AUX (pin 4,6,8,10,17,18) only for Remote ON/OFF used. This output is not controlled by the Remote ON/OFF control.
3	T-ALARM	High (3.5 ~ 5.5V) : When the internal temperature exceeds the limit of temperature alarm. Low (-0.5 ~ 0.5V) : When the internal temperature is normal. The maximum sourcing current is 10mA and only for output.(Note)
4,6,8,10	GND-AUX	Auxiliary voltage output GND. The signal return is isolated from the output terminals (+V & -V).
5	Fan Fail	High(3.5~5.5V):When the fan fail. Low(-0.5~0.5V):When the fan works normally. The maximum sourcing current is 10mA and only for output.(Note)
7	DC-OK	High(3.5 ~ 5.5V) : When $V_{out} \leq 80\% \pm 6\%$ . Low(-0.5 ~ 0.5V) : When $V_{out} \geq 80\% \pm 6\%$ . The maximum sourcing current is 10mA and only for output.(Note)
9	AC-OK	High (3.5 ~ 5.5V): When AC input $\geq 335 \pm 1.5\%$ Vac, PSU works normally. Low (-0.5 ~ 0.5V): When AC input $\leq 320 \pm 1.5\%$ Vac, PSU shut down. The maximum sourcing current is 10mA and only for output.(Note)
11,12	SCL/CANL/ DATA-	For PMBus model: Serial Clock used in the PMBus interface.(Note) For CANBus model: Data line used in CANBus interface.(Note) For MODBus model: Data line used in MODBus interface.(Note)
13,14	SDA/CANH/ DATA+	For PMBus model: Serial Data used in the PMBus interface.(Note) For CANBus model: Data line used in CANBus interface.(Note) For MODBus model: Data line used in MODBus interface.(Note)
15,16	+12V-AUX	Auxiliary voltage output, 11.4~12.6V, referenced to GND-AUX (pin17 & 18). The maximum load current is 1A. This output is not controlled by "Remote ON-OFF".
17,18	GND-AUX	Auxiliary voltage output GND. The signal return is isolated from the output terminals(+V & -V).

Note: Isolated signal, referenced to (GND-AUX).

## ※LED Status Indicators

LED	Description
Green(LED1)	LED on when output voltage is OK
Red(LED2)	LED on when any protection occurs

## ※AC Input Terminal Pin No. Assignment (TB1)

Pin No.	Assignment	Diagram	Maximum mounting torque
1	FG $\pm$		
2	AC/L1		
3	AC/L2		
4	AC/L3		18Kgf-cm

## ※DIP Switch Position Assignment(DIP-SW1): Please refer to the Function Manual.


Pin No.	Assignment	Diagram
1	DA,DB Signal and paralleled control function	
2	Output Current Programming (PC)	ON OFF
3	Output Voltage Programming (PV)	DIP-SW PIN2:PC DIP-SW PIN3:PV

## ※DIP Switch Position Assignment(DIP-SW81): Please refer to the Function Manual.

Pin No.	Function	Description
1	A0	
2	A1	PMBus/CANBus/MODBus interface address switch. (Max. 8 address)
3	A2	
4	RL	Termination resistors( $120\ \Omega$ ) for communication.(CANBUS、MODBUS). ON: connect; OFF: disconnect.

## ■ GUIDANCE OF ADDITIONAL FILTER

## 1.Schematic



 2.Minimum insertion loss (In dB at  $50\ \Omega$  system): Filter model FN3288-20-33-C35-R65 or equivalent

FREQ. MHz	0.01	0.05	0.10	0.15	0.50	1.0	5.0	10	30
COM. MODE dB	20	47	61	66	100	83	62	49	30
DIF. MODE dB	13	16	47	58	87	86	80	79	65

## 3.Minimum Impedance: Core model 4A11 or equivalent

FREQ. MHz	10	20	30	50	60	80	90	100	120
Z( $\Omega$ )	70.5	93.7	111	136	145	156	160	166	180

## 4.Configuration



## 1. Suitable for water cooling (L type)

Ambient temperature: 50°C

Inlet temperature: 5~15°C



Flow rate (minimum): 4~10LPM

Humidity: 20~90% RH non-condensing

Pressure drop 6 psi (minimum), pressure inlet 80 psi (maximum)

If optional cold plate is in need, please contact MEAN WELL for details.

Ordering No.: HS-684




Apply thermal grease (gap filler) between power supply and cold plate connection surface.

Thermal grease (gap filler):

\* Thermal conductivity is no less than 1W/mK.

\* Thickness is no more than 0.3mm.



2. With 85CFM FAN x 2 (L type)

