

FS Fixing mounting base 30080

CE
6/2022

Installation Guide:

- Drill a 6 mm Ø hole
- Wrap the DKS around the cable
- Insert DKS into FS Fixing mounting base longitudinally or in the transverse direction
- Insert the DKS with the FS into the drill hole.

Product details:

Colour	light grey
Content pack/box	200 / 4.000

Mounting and usage instructions:

Cover the Cable(s) with DKS and insert DKS into FS Fixing mounting base. Insert DKS into a 6 mm drill hole longitudinally to the cable if fixed distance of 21 mm is requested or mount it in the transverse direction to the cable if fixed distance of 8 mm is requested. Drill. Fasten. Done!

Technical data:

Material	PP, UV stabilised Temperature range: -10 °C up to +85 °C silicon-free Material tested according OVR R14 (LSFOH)
----------	---

Weight per piece 1,20 g

GTIN (EAN) 
9 008439 400805



With the FS Fixing mounting base in connection with the DKS Dowel clamp, the effortless mounting of thermal conduction cables with a fixed distance of 8 or 21 mm to the ceiling is possible.

 **Schnabl®**
time saving products

Schnabl Stecktechnik GmbH, Bahnhofplatz 1, po box 63, 3100 St. Pölten, Austria
Telephone +43 2742 22167-0. office@schnabl.works. www.schnabl.works

Only the
ORIGINAL is
ingenious

