



■ Features :

- AC input 180~264VAC only
- 130% peak load capability
- 110mm slim design
- Built-in active PFC function compliance to EN61000-3-2
- High efficiency 94% and low power dissipation
- Protections: Short circuit / Overload / Over voltage / Over temperature
- Cooling by free air convection
- Built-in constant current limiting circuit
- Can be installed on DIN rail TS-35/7.5 or 15
- UL508(industrial control equipment)approved
- EN61000-6-2(EN50082-2) industrial immunity level
- Current sharing up to 3840W(3+1)
- Built-in DC OK relay contact
- 100% full load burn-in test
- 3 years warranty




CB CE

SPECIFICATION

MODEL	SDR-960-24	SDR-960-48
OUTPUT	DC VOLTAGE	24V
	RATED CURRENT	40A
	CURRENT RANGE	0 ~ 40A
	RATED POWER	960W
	PEAK CURRENT	52A
	PEAK POWER Note.6	1248W (3sec.)
	RIPPLE & NOISE (max.) Note.2	180mVp-p
	VOLTAGE ADJ. RANGE	24 ~ 28V
	VOLTAGE TOLERANCE Note.3	±1.0%
	LINE REGULATION	±0.5%
INPUT	LOAD REGULATION	±1.0%
	SETUP, RISE TIME	1000ms, 100ms/230VAC at full load
	HOLD UP TIME (Typ.)	14ms / 230VAC at full load
	VOLTAGE RANGE Note.7	180 ~ 264VAC 254 ~ 370VDC
	FREQUENCY RANGE	47 ~ 63Hz
PROTECTION	POWER FACTOR (Typ.)	PF ≥ 0.95/230VAC at full load
	EFFICIENCY (Typ.)	94%
	AC CURRENT (Typ.)	6A/230VAC
	INRUSH CURRENT (Typ.)	COLD START 50A / 230VAC
	LEAKAGE CURRENT	<3.5mA / 240VAC
FUNCTION	OVERLOAD	Normally works within 105 ~ 130% rated output power for more than 3 seconds and then shut down o/p voltage with auto-recovery after 30 seconds if the peak load condition is removed
		Constant current limiting within 130 ~ 150% rated output power for more than 3 seconds and then shut down o/p voltage, re-power on to recover
	OVER VOLTAGE	29 ~ 33V
		Protection type : Shut down o/p voltage, with auto-recovery or re-power on to recover
	OVER TEMPERATURE	90°C ±5°C (TSW) detect on heatsink of power switch
ENVIRONMENT		Protection type : Shut down o/p voltage, recovers automatically after temperature goes down
	DC OK REALY CONTACT RATINGS (max.)	60Vdc/0.3A, 30Vdc/1A, 30Vac/0.5A resistive load
	CURRENT SHARING	Please refer to function manual
	WORKING TEMP. Note.5	-30 ~ +70°C (Refer to "Derating Curve")
	WORKING HUMIDITY	20 ~ 95% RH non-condensing
SAFETY & EMC (Note 4)	STORAGE TEMP., HUMIDITY	-40 ~ +85°C, 10 ~ 95% RH
	TEMP. COEFFICIENT	±0.03%/°C (0 ~ 50°C)
	VIBRATION	Component:10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes; Mounting: Compliance to IEC60068-2-6
	SAFETY STANDARDS	UL508, TUV EN60950-1 approved
OTHERS	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC O/P-DC OK:0.5KVAC
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:>100M Ohms / 500VDC / 25°C / 70% RH
	EMC EMISSION Note.8	Compliance to EN55022 (CISPR22), EN61204-3 Conduction class B, Radiation class A, EN61000-3-2,-3
NOTES	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, EN55024, EN61000-6-2 (EN50082-2), EN61204-3, heavy industry level, criteria A
	MTBF	69.8K hrs min. MIL-HDBK-217F (25°C)
	DIMENSION	110*125.2*150mm (W*H*D)
NOTE	PACKING	2.47Kg ; 6pcs/15.8Kg/1.55CUFT
	1.	All parameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature.
	2.	Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor.
	3.	Tolerance : includes set up tolerance, line regulation and load regulation.
	4.	The power supply is considered a component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets EMC directives.
	5.	Installation clearances : 40mm on top, 20mm on the bottom, 5mm on the left and right side are recommended when loaded permanently with full power. In case the adjacent device is a heat source, 15mm clearance is recommended.
	6.	3 seconds peak power max. and the average output power should not exceed the rate power.
	7.	Derating may be needed under low input voltage. Please check the derating curve for more details.
	8.	Consult MEAN WELL for deployment of Radiation class B.

■ Mechanical Specification

Case No.214A Unit:mm



ADMISSIBLE DIN-RAIL:TS35/7.5 OR TS35/15

Terminal Pin No. Assignment (TB1)

Pin No.	Assignment
1	FG (Ground)
2	AC/N
3	AC/L


Terminal Pin No. Assignment (TB2)

Pin No.	Assignment
1,2,3	DC OUTPUT +V
4,5,6	DC OUTPUT -V

Control Pin (CN205) : DINKLE ECH250R-04P or equivalent

Pin No.	Assignment	Mating Housing	Wire Diameter
1	P-(Current Share)	DINKLE ECH250R-04P	0.081~0.517mm ²
2	P+(Current Share)	or equivalent (Including in the single package)	(28~20AWG)
3,4	DC OK Relay Contact		



■ Block Diagram




■ DC OK Relay Contact

Contact Close	PSU turns on / DC OK.
Contact Open	PSU turns off / DC Fail.
Contact Ratings (max.)	30V/1A resistive load.


■ Peak Loading



■ Derating Curve



■ Output derating VS input voltage



■ Function Manual

1. Current sharing

- (1) Parallel operation is available by connecting the units shown as below (P+, P- are connected mutually in parallel).
- (2) Difference of output voltages among parallel units should be less than 0.2V.
- (3) The total output current must not exceed the value determined by the following equation (Output current at parallel operation)=(The rated current per unit) x (Number of unit) x 0.9.
- (4) In parallel operation 4 units is the maximum, please consult the manufacturer for other applications.
- (5) The power supplies should be paralleled using short and large diameter wiring and then connected to the load.
- (6) When in parallel operation, the minimum output load should be greater than 5% of total output load.
(Min. load >5% rated current per unit x number of unit)
- (7) In parallel connection, maybe only one unit (master) operate if the total output load is less than 5% of rated load condition.
The other PSUs (slaves) may go into standby mode and their output LEDs & relays will not turn on.
- (8) Some minor noise may be heard at light load condition under parallel operation.
This is a normal phenomenon and the performance of the PSU will not be influenced.

